

USB-COUNT

8 channel frequency counter, max. 500kHz via USB.
Pulse count up/down or phase A/B. Powered from USB port

FEATURES

Versatile frequency counter, pulse counter via the USB port
Powered from the USB port
A total of 8 entries, of which:
4 channels for UP/DOWN, DIR/PULSE, Phase AB
8 channels for Count-Up and frequency counter
32 bit resolution
Max. 500kHz (non-isolated)
Input voltage: 0 - +30V
USB 2.0
YOUR assembly
Dimensions: 107 x 102 x 33 mm
Operating temperature: -25 - + 75°C



Danbit A/S Schous plass 1 Oslo, N-0552
Norway



67 104 460



salg@danbit.dk

USB-COUNT

SPECIFICATIONS

Forsyning	:	Via USB porten
Indgang	:	Ikke isoleret Logisk 0: 0 - 0,8 V, Logisk 1: 2 - 5 V. Isoleret Logisk 0: 0 - 1 V Logisk 1: 4,5 - 30 V
Isolation	:	2500 VDC
Montering	:	DIN-skinne
Software	:	USB driver til Windows 2000,XP, Win7 og Win8
Stik	:	USB type B og skrueterminaler
Dimensioner	:	102 x 33 x 107 mm

