

M485-ETH-HART-I

Ethernet to HART converter - Master. Allows 2 Masters. Gateway.

FEATURES

Supports HART short / long frame Supports HART Burst mode Supports point-to-point or multi-drop HART mode Supports connection of up to 15 HART slave devices Allow 2 HART masters The HC_Tool tool for module configuration and HART communication Supports firmware update via Ethernet PWR / TxRx indication LED 4KV ESD protection Built-in watchdog Selectable 250 Ω load resistor 4 HART channels Support VxComm technique Built-in web server for network setting







M485-ETH-HART-I

SPECIFICATIONS Operating Temp.	-25 °C ~ +75 °C
operating reinp.	23 6 173 6
Andet	Selectable 250 Ω terminal resistor for each HART port.Power reverse polarity protection, Over-voltage brown-out protection
Ethernet	10/100 Base-TX with Auto MDI/MDI-X
Isolation	500 VDC
Kanaler	4
LED	PWR : Power Indicator TxRx : Data Received from Ethernet / HART Indicator
Luftfugtighed	5% ~ 95% RH, non-condensing
Montering	DIN-Rail or Wall Mounting
Stik	2-pin screwed terminal block for each HART port





67 104 460



salg@danbit.dk