

**USB-KEY6SW**

**X-KEYS - Programmable USB switch box to 6 / 12 (dual cable) external contacts. USB HID commands. acquisition contacts**

**FEATURES****USB Switch interface**

6 input ports for push buttons with 3.5mm jack connector.

3.5mm Jack is stereo and can handle 2 push buttons

if 12 push buttons, then with optional splitter cable

For USB Port

**Mounting Flanges**

Any button pressure can trigger USB HID command

Software for button macro programming

setup lies in the device



Danbit A/S Schous plass 1 Oslo, N-0552  
Norway



67 104 460



salg@danbit.dk

## USB-KEY6SW

**SPECIFICATIONS**

Operating Temp.	:	-20 to 60 C
Farve	:	Black
Andet	:	HID keyboard, HID mouse, HID game controller, HID multimedia
Forsyning	:	Power Source USB port, nominal voltage - 5 VDC Power Consumption 21 mA @ 5 VDC
Features	:	Programmable
IP-Tæthed	:	IP 40, typical indoor office environment
OS SUPPORT	:	Use: Any OS via USB HID   Programming: Windows XP through 10, Mac OS X 10.4 through 10.10
Porte	:	6 ports (split to 12 with optional Y cords)
Software	:	Windows: MacroWorks 3.1 Android: X-keys Android Mac OS X: ControllerMate
Stik	:	Wired USB 2.0 standard "A" plug
Tilslutning	:	USB
Weight	:	160 g





**DANBIT**

USB-KEY6SW

## SPECIFICATIONS



Danbit A/S Schous plass 1 Oslo, N-0552  
Norway



67 104 460



salg@danbit.dk

For business customers only (B2B). Prices exclude VAT. We reserve the right to correct errors and make changes.