

M485-AD16U8-I

8 x analoge differensielle innganger, 0 - 20mA, +/- 10 volt, 16bit løsning, samplehastighet 10Hz, RS485. 10 - 30VDC.

FEATURES

- 8 kanal analog input modul til RS485 bus
- 16bit opløsning
- 10 målinger per sekund (total)
- For strømmåling - shunt med 125 ohm modstand
- Forsyningsspænding: 10 - 30VDC / 1.3 Watt
- Mål: 123 x 72 x 35 mm
- Med DIN beslag



Danbit A/S Schous plass 1 Oslo, N-0552
Norway



67 104 460



salg@danbit.dk

SPECIFICATIONS

Forsyning	:	10 - 30 VDC, 1,2 W via klemrække
Indgangsimpedans	:	20 MΩ
Isolation	:	3000 VDC
Maks. hastighed	:	10 målinger pr. sek. (totalt på alle 8 indgange)
Måleområde	:	±150 mV, ±500 mV ±1 V, ±5 V, ±10 V samt ±20 mA
Opløsning	:	16 bit, ±0,1% præcision
Stabilitet	:	Nulpunktsdrift: ±6 µV/°C Drift af følsomhed: ±25 ppm/°C

