

M485-DA4-I

4 x analoge utganger, +/- 10 volt, 0-20mA, 12bit,
RS485 buss

FEATURES

RS485 Modul med 4 analoge utganger
0-20mA eller 0 - +/- 10V
D / A Svarstid: 10ms
Oppløsning: 14 bit
Spenning: 10 - 30VDC



Danbit A/S Schous plass 1 Oslo, N-0552
Norway



67 104 460



salg@danbit.dk

M485-DA4-I

SPECIFICATIONS

Forsyning	:	10 - 30 VDC, 1,4 W
Isolation	:	3000 VDC
Opløsning	:	12 bit, $\pm 0,1\%$ præcision(mA) $\pm 0,2 \%$ (V)
Stabilitet	:	Nulpunktsdrift: Spænding: $\pm 30 \mu\text{V}/^\circ\text{C}$ Strøm: $\pm 0,2 \mu\text{A}/^\circ\text{C}$. Kontrolmåling af udsendt værdi: $\pm 1 \%$ Drift af følsomhed: $\pm 25 \text{ ppm}/^\circ\text{C}$
Udgange	:	± 10 , ± 5 , 0-5, 0 -10 volt., 0- 20 og 4 - 20 mA



Danbit A/S Schous plass 1 Oslo, N-0552
Norway



67 104 460



salg@danbit.dk