

I-7014D

I-7014D 1-channel Transmitter Input with 7-segment LED Display using the DCON and Modbus Protocols (Blue Cover)

FEATURES

The I-7014 is a 1-channel Transmitter Input module that provides a +15 VDC isolated loop power supply for transmitter input, and is designed for both voltage and current input types. In addition, the module provides 1 Digital Input channel as a 50 Hz event counter and 2 Digital Output channels that can be used as a high/low alarm. The I-7014 also features 3000 VDC intra-module isolation.



Danbit A/S Schous plass 1 Oslo, N-0552
Norway



67 104 460



salg@danbit.dk