

SW8BNC-1COMP

8 x BNC Composite video inputs for 1 x BNC output,
push button selection and remote control
FEATURES

Composite Video Switch
8 Input BNC Hier to 1 Output BNC He
Supports lower power consumption at full load
below 500 mA
AC / DC Adapter- 12 VDC, 300 mA
Video Distortion: 0 .5 DB
Remote control IR
for wall mounting
175 x 81 x 25 mm



Danbit A/S Schous plass 1 Oslo, N-0552
Norway



67 104 460



salg@danbit.dk

SPECIFICATIONS

Andet	:	Menu & IR Remote controller
Forsyning	:	12 VDC @300 to 1000 mA
Input	:	8x BNC female port
Isolation	:	60 dB, 6.5 dB Gain between any input and output
LED	:	Control by front pushbuttons with LCD readout
Montering	:	Metal: Wall mountable ear panels attached
Opsætning	:	Easy to install and simple to operate
Output	:	1x BNC female port
Tilbehør	:	Remote control
Trådløs	:	IR Frequency 38 KHz
Weight	:	0.49 kg
Dimensioner	:	17.5 x 8.1 x 2.5 cm

