

BOOST-HDMI150-U+IR

HDMI KVM extender, 150 meters over Cat 6a / 7 RJ45 cable, or over TCP/IP, USB HID

FEATURES

Transmits HDMI video and audio and USB up to 150 meters over network cable

Transfers HDMI video and audio and USB over local network

USB is for keyboard and mouse only Set with transmitter and receiver

1920 x 1080 @60Hz A transmitter to multiple receivers over non-

managed switch.
Supports keyboard and mouse ONLY
Supports TCP/IP and local EDID

HDMI 1.3 / HDCP 1.2

Transmitter: 1 x HDMI, 1 x USB-B, 1 x RJ45 Ethernet Receiver: 1 x HDMI, 2 x USB-A, 1 x RJ45 Ethernet

built-in auto-adjustment system Built-in ESD protection system Power supply: DC 5V/1A (supplied) Dimensions: 92 x 70 x 25 mm





BOOST-HDMI150-U+IR

SPECIFICATIONS	
USB	PC: Type B USB interface; connect to PC; K/M: connect USB keyboard and mouse;
Operating Temp.	-5~ +70
Indgang	HDMI-A
Netværk	RJ45 CAT 6 - 150 meter- Cat7 - 180 meter
Opløsning	1920X1080@60Hz
Strømforbrug	MAX 3W
Strømforsyning	DC 5V/1A
Dimensioner	92*70*25mm





67 104 460



salg@danbit.dk