

BOOST-HDMI120+IR

HDMI KVM extender, 120 meters over Cat 5/6 RJ45,
TCP/IP, USB

FEATURES

- Transfers HDMI video and sound and USB up to 120 meters above network cable
- Transfer HDMI video and audio and USB over LAN networks
- Set with transmitter and receiver
- 1920 x 1080 @ 60Hz
- Supporter and mice
- Supporter TCP / IP and Local Edid
- Supporter IR
- HDMI 1.3 / HDCP 1.2
- Transmitter: 1 x HDMI, 1 x USB-B, 1 x RJ45 Ethernet
- Receiver: 1 X HDMI, 2 x USB-A, 1 x RJ45 Ethernet
- Built-in auto adjustment system
- Built-in ESD protection system
- Power supply: DC 5V / 2A (supplied)



Danbit A/S Schous plass 1 Oslo, N-0552
Norway



67 104 460



salg@danbit.dk

BOOST-HDMI120+IR

SPECIFICATIONS

USB	:	PC: Type B USB interface; connect to PC; K/M: connect USB keyboard and mouse;
Operating Temp.	:	-5~ +70
Indgang	:	HDMI-A
Netværk	:	RJ45 CAT 6 - 120 meter
Opløsning	:	1920X1080@60Hz
Strømforbrug	:	MAX 3W
Strømforsyning	:	DC 5V/1A



Danbit A/S Schous plass 1 Oslo, N-0552
Norway



67 104 460



salg@danbit.dk