

BOOST-HDMI150-U-IRT

KVM Extender over RJ45 up to 200m, HDMI & USB

FEATURES

- Transmitter to BOOST-HDMI150-U-IRR receiver
- Transmits HDMI video and audio and USB up to 150 meters over network cable
- Transmits HDMI video and audio and USB over local network
- USB is only for keyboard and mouse
- Sends 1920x1080 @60Hz
- One transmitter to multiple receivers over non-managed switch.
- Supports keyboard and mouse ONLY
- Supports TCP/IP and local EDID
- HDMI 1.3 / HDCP 1.2
- Transmitter: 1 x HDMI, 1 x USB-B, 1 x RJ45 Ethernet
- Built-in ESD protection system
- Power supply: DC 5V/1A (included)
- Dimensions: 92 x 70 x 25 mm



Danbit A/S Schous plass 1 Oslo, N-0552
Norway



67 104 460



salg@danbit.dk