

BOOST-HDMI150-U-IRR

HDMI KVM extender receiver, 150 meters over Cat 6a RJ45 cable, or over TCP/IP, USB HID. FEATURES

Receiver to transmitter BOOST-HDMI150-U-IRT HDMI video and audio and USB up to 150 meters over network cable

HDMI video and audio and USB over local network USB is only for keyboard and mouse Recipient

1920x1080 @60Hz

Multiple receivers to transmitter over non-managed switch.

Supports keyboard and mouse ONLY Supports TCP/IP and local EDID

HDMI 1.3 / HDCP 1.2

Receiver: 1 x HDMI, 2 x USB-A, 1 x RJ45 Ethernet

built-in auto-adjustment system Built-in ESD protection system Power supply: DC 5V/1A (included) Dimensions: 92 x 70 x 25 mm

