

BOOST-USB600-1.1

USB Keyboard & Mouse CAT5e Extender 600 m FEATURES

Extends USB keyboard & mouse (HID) over CAT5e up to 600 m

Transmitter is bus-powered (no external power needed under 30 m)


Receiver side powered via DC 5V supply

Supports USB 1.1 for HID devices (keyboard & mouse)

Plug-and-play operation with no drivers or software Compact form factor suitable for professional installations









67 104 460



salg@danbit.dk



BOOST-USB600-1.1

SPECIFICATIONS

Input : TX: 1 x USB Type A, RX: 1 x RJ45

Output : TX: 1 x RJ45, RX: 1 x USB Type A

Operating Temperature : 0°C to 55°C

Power Supply : DC 5V 1A