

6 x Digital input 6 x Relay output via Ethernet for industrial control applications. 2 x RJ45 Daisy Chain
10 - 30VDC

FEATURES

- 6 x Digital Inputs - Wet (active at DC in)
- 6 x Power relay outputs - 24VDC / 250VAC / 5A
- Protocol: Modbus TCP / UDP
- 2 x RJ45 Ethernet interface
- With built-in network switch - with the daisy chain
- I/O Pair-function - the input is mirrored to the second output
- Digital inputs with counter - max 500Hz
- the minimum pulse width: 1 ms
- Screw terminal
- Supply voltage: 10 - 30VDC / 3watt



ETHIO6I6PR-2I

SPECIFICATIONS

Forsyning	:	10 - 30 VDC, 2,5 W via klemrække
Indgang	:	6 stk. digitale Logisk 0: 0 - 4 VDC, Logisk 1: 10 - 50 VDC
Netværk	:	10/100 Mbit m/RJ45-stik
Udgange	:	6 stk. relæudgange: AC: 250 V og 5 A eller DC: 30 V og 5 A. Skiftetider Lukke/åben er 7ms / 3 ms



Danbit A/S Schous plass 1 Oslo, N-0552
Norway



67 104 460



salg@danbit.dk