

X-KEYS - Programmable USB-koblingskasse til 6 /12
(dual kabel) utvendige kontakter. USB HID-
kommandoer. Kjøp kontakter

FEATURES

- USB switch interface
- 6 input porte til trykknapper med 3,5mm Jack stik.
- 3.5mm Jack er stereo og kan håndtere 2 trykknapper
- Hvis 12 trykknapper, så med optional splitter-kabel
- Til USB port
- Mounterings-flanger
- Hvilken som helst knaptryk kan udløse USB HID kommando
- Software til knap-makro-programmering
- Opsætning ligger i enheden



SPECIFICATIONS

Driftstemperatur	:	-20 to 60 C
Farve	:	Black
Annen	:	HID keyboard, HID mouse, HID game controller, HID multimedia
Forsyning	:	Power Source USB port, nominal voltage - 5 VDC Power Consumption 21 mA @ 5 VDC
Funktioner	:	Programmable
IP-Tæthed	:	IP 40, typical indoor office environment
OS SUPPORT	:	Use: Any OS via USB HID Programming: Windows XP through 10, Mac OS X 10.4 through 10.10
Porte	:	6 ports (split to 12 with optional Y cords)
Software	:	Windows: MacroWorks 3.1 Android: X-keys Android Mac OS X: ControllerMate
Stik	:	Wired USB 2.0 standard "A" plug
Tilslutning	:	USB
Vekt	:	160 g



**DANBIT**

USB-KEY6SW

SPECIFICATIONS



Danbit A/S Schous plass 1 Oslo, N-0552
Norway



67 104 460



salg@danbit.dk

For business customers only (B2B). Prices exclude VAT. We reserve the right to correct errors and make changes.