

Utendørs trådløs PIR sensor - infrarød bevegelsessensor med antenne, batteridrevet, 35 m FEATURES

- Trådløs infrarød utendørs PIR-bevegelsessensor
- Ekstern antenne
- Justerbar områdesensor 10-35m / 750 kvm
- Batteridrevet 2 x AAA 1,5 volt
- Driftstemperatur -20 til + 55 °
- IP55 nær 150 meter synsfylt
- Til veggmontering (inkludert tilbehør)
- Systemet virker ikke uten mottaker PIR-WL-R



SPECIFICATIONS

Driftstemperatur	:	-20° C + 55° C
Annen	:	Digital integral white light filter. 16 million possible identification codes Adjustments Detection signal (CCTV) timer 0.4 to 60 secs. Light level signal 2 Lux to daylight. Pulse count 1 (2 & 3 - 6 seconds)
Batteri	:	2 x AAA (not included)
Batteri	:	Ca. 2 år
IP-Tæthed	:	Detector Housing ABS high impact IP55 rated
Montering	:	3m high for multibeam coverage, 6m high for curtain coverage and 1.5m with mask for pet immunity
Rækkevidde	:	Transmission 150 metres line-of-sight: 433.92 MHz frequency - SAW stabilised
Sensor	:	Coverage Range 10 to 35 metres: 35 x 30 m with 90° multi function lens
Vekt	:	152g
Dimensioner	:	110 x 100 x 100mm (HxWxD)

